



- auxiliary relay for extension of the field disconnector of the Nefa 16-plus F/1 series
- for controlling 3~ phase appliances (electric cooker) or for switching off several circuits simultaneously
- The HR4S auxiliary relay is an extension of the NA 16-1P radio field disconnection switch to also switch off 3~ (400V) consumers, such as an electric cooker or several circuits simultaneously.
- The auxiliary relay HR4S is mounted next to the field disconnector in the power distribution box and controlled by its output. Not suitable for automatic demand switches.

Order-No.: 720053

Short-Desc.: HR4S

Accessories Radio demand switch

Auxiliary relay HR4S

Technical data

length:	85 mm
width:	35 mm (2 TE)
height:	60 mm
colour:	light grey
control voltage:	230 V
rated current:	25 A
operating voltage:	400 V
connection cross-section:	rigid (1 - 10 mm ²) flexible (1 - 6 mm ²)
switching contacts:	4 NO contacts
approvals:	VDE DIN EN 61095 (VDE 0637-3) DIN VDE 0106-100
other features:	hum-free screw technology

Scope of application

extension for the field disconnector of the series:
NA 16-1P Funk

Scope of delivery

auxiliary relay HR4S